

POWERPAX 500



- **Mobile AC and DC Power Supply**
- **12 to 24 VDC (factory set) 60W peripheral supply**
- **30W, 12VDC cigarette lighter output or 110VAC output via inverter**
- **Accepts 10 to 30 VDC power inputs**
- **Optional (24 VDC) HumVee Power cable**
- **Accepts 90 to 264VAC power inputs**

POWERPAX™ 500 MOBILE POWER SUPPLY

The Powerpax™ 500 mobile power supply provides a factory set 12 to 24VDC (60W) output to run your laptop or other peripheral, providing a UPS capability of up to 30-Watt hours.

In addition the PowerPax™ 500 is fitted with a 30W 110VAC inverter output and a 12VDC cigarette output to supply additional AC or DC equipment such as cameras, scanners and printers.

The Powerpax™ 500 is ideally suited for mobile applications where power supplies are often noisy and unreliable or where your only source of power is your vehicle or boat etc.

The Powerpax™ 500 will guarantee you stay operational for longer anywhere in the world.

SPECIFICATION POWERPAX™ 500

DC Input	10 to 30 VDC
AC Input	90 to 264 VAC
Laptop* Output	Factory set 12 to 24 VDC * NB. Could be set for other peripherals
AC Output	110VAC 30W via US mains power socket
DC Output	12DC via vehicle cigarette lighter connector
Size	12" W x 11.5" D x 2.4" H (305mm W x 292mm D x 62mm H)
Weight	8.9lbs, 4.0Kg



PowerPax 500 Rear with HumVee Power Cable Connected

**For more information contact:
Action Systems, a division of V&A Incorporated
480 North 17th Street
Las Cruces, New Mexico 88005**